



85741139



IP20

Blind time switch with display, Berker R.1/R.3/R.8/Serie 1930/R.classic, polar white glossy

Technical features

Functions

Astronomic time shift	± 2 h
Running time	2 mn
Random number generator	± 15 mn
Power reserve	≈ 24 h
<ul style="list-style-type: none"> - reset function (to factory setting) - with keylock - Party function, no execution of automatic, radio and extension unit commands (lock-out protection) - with switchover manual/automatic mode 	

Controls and indicators

- LC display illuminated during operation
- indication of the application module/insert compatibility in the display
- LC display contrast is adjustable

Main electrical features

Nominal voltage	12 V
Frequency	- Hz

Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

Detection

- Not suitable for rain and wind sensors

Materials

Colour of design line	polar white
Colour	polarwhite
Material	Plastic/metal

Dimensions

Diameter	58 mm
----------	-------

Installation, mounting

Installation mode	clamp fastening
-------------------	-----------------

Settings

Minimum slat adjustment time	≈ 250 ms
Lamella adjustment on button-press	< 0,5 s
Time	with automatic summer-/winter time switching (can be switched off)

- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable
- holiday programme for random variation of the operation times in automatic operation

Equipment

Number of operation times for up/down	20
Self-retaining for 2 min on button-press	> 0,5 s
Change-over time for change of direction	< 0,6 s
- 2 independent preset programme memories, individually adaptable	

Use

Differentiation characteristic 2 - Sales	with display
--	--------------

Safety

- with dismantling protection

Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

Identification

Application, usage	Blind control
Main design line	Berker R.1/R.3/R.8/Serie 1930/R.classic
Secondary design line(s)	Electronics platform, Berker R.1, Berker R.3, Berker R.8

Instructions

- Note:
When integrating this product into the Serie 1930, the 1gang frame for centre plate Ø 58 mm, order no.: 1382 0... may only be used. Installation in multiple combinations of the Serie 1930 is not possible!
- Can be switched to orientation led by extension unit.