

Communication technology

Communication technology



450009

TAE socket outlet 3x6 NFN Communication technology, polar white matt

Technical features

Identification

Application, usage

Main design line

| Design | according to DIN 41715 |
|--------------------------------------|------------------------|
| - 3 x 6pole for 1 outside line | · |
| Connectivity | |
| - with straight outlet | |
| Main electrical features | |
| Rated voltage | 125 V |
| | |
| Power | |
| Load per circuit | max. 10 V <i>A</i> |
| Resistance | |
| Transition resistance | < 20/30 mΩ |
| Materials | |
| Colour of design line | polar white |
| Colour | polarwhite |
| Material | Plastic/meta |
| Surface appearance | mat |
| Dimensions | |
| Insertion depth | 22 mm |
| Installation, mounting | |
| Installation mode | with spreader claws |
| Connection | |
| - with screw terminals | |
| Cable | |
| Conductor Ø | max. 1 mm |
| Equipment | |
| - for 1 telephone and 2 add-on units | |